



# Approved Meter Equipment Enclosure List:

Revised  
4/6/2012

The attached list of self-contained meter sockets and enclosures has been approved for use in the service areas served by the utilities of the Florida Meter Group. Approval is based on the unit's compliance with the FMG specifications, particularly U.L. listing, sealing requirements, bypass characteristics, and certain operational concerns. FMG makes no claims regarding nameplate ratings or load side attachments beyond the sealed portion of the meter socket. We recommend that all units be used as intended by the manufacturer. All additional data is supplied for informational purposes only.

### NOTES:

- A. All commercial or three phase applications require a unit with an approved bypass device. (Configuration 3, 4 or 5)
- B. All sockets are listed as their maximum socket amperage. 320/400 Amp enclosures are listed as 400 Amp maximum and 480/600 Amp enclosures are listed as 600 Amp maximum.
- C. Aluminum enclosures are recommended in salt spray areas.
- D. Sealing rings (ring-type sockets) along with all lugs/connectors (line and load side) are considered to be part of the meter enclosure. The customer/contractor is thereby responsible for furnishing these items. Please contact your utility representative to determine the proper size lugs/connectors. The sealing ring must be a captive-screw type equivalent to ABB #01L0028G02, Milbank MR-4/A3068, Landis & Gyr #9738-8002, or Ekstrom 10-9090.
- E. The "configuration" refers to the various meter connecting arrangements used to accommodate the utility meter. These configurations are described below:

### SELF CONTAINED CONFIGURATIONS

### DESCRIPTION & TYPICAL APPLICATION

1	Residential - 4 Terminal Socket, Single Phase, 3 Wire
2	Residential - 5 Terminal Socket, Network, 3 Wire
3	Residential/Commercial - 4 Terminal Socket (w/Bypass), Single Phase, 3 Wire
3a	Residential/Commercial - 5 Terminal Socket (w/Bypass), Network, 3 Wire
4	Commercial - 7 Terminal Socket (w/Bypass), Three Phase, 4 Wire
*5	Residential/Commercial – K7 Base (w/Bypass), Single Phase (FPL Only), Three Phase or Network, 3 or 4 Wire

**\*K7 Three Phase K-Base applications are ONLY allowed at FPL (GULF, PEF, and TECO do not allow any K-base installations)**

Participants:





Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number		Phase	Service	Pos	Term	Bypass	Config
Durham	100	UTZ-6R1131C-FL		1	Ov/Un	6	5	N	1,2
Durham	100	UTZ-xR1121C-FL	(where x=2-5)	1	Ov/Un	2-5	4/5	N	1,2
Durham	125	UATZ-RS101C-FL		1	Ov/Un	1	4/5	N	1,2 AI
Durham	125	UTZ-RS101C-FL		1	Ov/Un	1	4/5	N	1,2
Durham	200	UAT-H4203x-FL	(where x=B or T)	1	Over	1	4	Y	1 AI
Durham	200	UAT-H4213x-FL	(where x=C or U)	1	Ov/Un	1	4	Y	1 AI
Durham	200	UAT-H5203x-FL	(where x=B or T)	1	Over	1	5	Y	3,3a AI
Durham	200	UAT-H5213x-FL	(where x=C or U)	1	Ov/Un	1	5	Y	3,3a AI
Durham	200	UAT-H7203x-FL	(where x=B or T)	3	Over	1	7	Y	4 AI
Durham	200	UAT-H7213x-FL	(where x=C or U)	3	Ov/Un	1	7	Y	4 AI
Durham	200	UAT-RS202B-FL		1	Over	1	4/5	N	1,2 AI
Durham	200	UAT-RS212C-FL		1	Ov/Un	1	4/5	N	1,2 AI
Durham	200	UAT-RS213A-FL		1	Under	1	4/5	N	1,2 AI
Durham	200	UAT-RS213C-FL		1	Ov/Un	1	4/5	N	1,2 AI
Durham	200	UAT-RS223A-FL		1	Under	1	4/5	N	1,2 AI
Durham	200	UT-4R2352U-FL		1	Ov/Un	4	4/5	N	1,2
Durham	200	UT-H4203x-FL	(where x=B or T)	1	Over	1	4	Y	1
Durham	200	UT-H4213x-FL	(where x=C or U)	1	Ov/Un	1	4	Y	1
Durham	200	UT-H5203x-FL	(where x=B or T)	1	Over	1	5	Y	3,3a
Durham	200	UT-H5213x-FL	(where x=C or U)	1	Ov/Un	1	5	Y	3,3a
Durham	200	UT-H7203x-FL	(where x=B or T)	3	Over	1	7	Y	4
Durham	200	UT-H7213x-FL	(where x=C or U)	3	Ov/Un	1	7	Y	4
Durham	200	UT-RS202B-FL		1	Over	1	4/5	N	1,2
Durham	200	UT-RS212C-FL		1	Ov/Un	1	4/5	N	1,2
Durham	200	UT-RS213A-FL		1	Under	1	4/5	N	1,2
Durham	200	UT-RS213C-FL		1	Ov/Un	1	4/5	N	1,2
Durham	200	UT-RS223A-FL		1	Under	1	4/5	N	1,2
Durham	200	UT-xR2332U-FL	(where x=2-3)	1	Ov/Un	2-3	4/5	N	1,2
Durham	200	UT-xR2392UU-FL	(where x=5-6)	1	Ov/Un	5-6	4/5	N	1,2
Durham	400	1008836		1	Ov/Un	1	4	Y	1
Durham	400	1008837		1	Ov/Un	1	4	Y	1 AI
Durham	400	UAT-H4300T-FL		1	Over	1	4	Y	1 AI
Durham	400	UAT-H5300T-FL		1	Over	1	5	Y	3,3a AI
Durham	400	UAT-H5330U-FL		1	Ov/Un	1	5	Y	3,3a AI
Durham	400	UAT-H7300T-FL		3	Over	1	7	Y	4 AI
Durham	400	UAT-H7330U-FL		3	Ov/Un	1	7	Y	4 AI
Durham	400	UT-H4300T-FL		1	Over	1	4	Y	1
Durham	400	UT-H5300T-FL		1	Over	1	5	Y	3,3a
Durham	400	UT-H5330U-FL		1	Ov/Un	1	5	Y	3,3a
Durham	400	UT-H7300T-FL		3	Over	1	7	Y	4



Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number	Phase	Service	Pos	Term	Bypass	Config	
Durham	400	UT-H7330U-FL	3	Ov/Un	1	7	Y	4	
Eaton-Cutler Hammer	100	UTZ-6R1131C-FLCH	1	Ov/Un	6	4/5	N	1,2	
Eaton-Cutler Hammer	100	UTZ-xR1121C-FLCH	(where x=2-5)	1	Ov/Un	2-5	4/5	N	1,2
Eaton-Cutler Hammer	125	1MMx12RRL or RRLC	(where x=3-6)	1	Ov/Un	3-6	4	N	1,2
Eaton-Cutler Hammer	125	1MP2122RRL or RRLC	1	Ov/Un	2	4	N	1,2	
Eaton-Cutler Hammer	125	1MPx124RRL or RRLC	(where x=3-4)	1	Ov/Un	3	4	N	1,2
Eaton-Cutler Hammer	125	1MPx126RRL or RRLC	(where x=5-6)	1	Ov/Un	5-6	4	N	1,2
Eaton-Cutler Hammer	125	3MMx12RRL or RRLC	(where x=2-6)	3	Ov/Un	2-6	4	N	1,2
Eaton-Cutler Hammer	125	CHR (POWER OUTLET PANEL)	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	125	CMB24L125BTS FLCH	1	Ov/Un	1	4/5	N	1,2	
Eaton-Cutler Hammer	125	MB24L125BTS FLCH	1	Ov/Un	1	4/5	N	1,2	
Eaton-Cutler Hammer	125	UATZ-RS101C-FLCH	1	Ov/Un	1	4/5	N	1,2 AI	
Eaton-Cutler Hammer	125	UTZ-RS101C-FLCH	1	Ov/Un	1	4/5	N	1,2	
Eaton-Cutler Hammer	150	CMB88B150BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	150	CMBB150BTS FLCH	1	Ov/Un	1	4/5	N	1,2	
Eaton-Cutler Hammer	150	MB816B150BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	150	MBB150BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	150	MBT48B150BTS	1	Ov/Un	1	4/5	N	1,2	
Eaton-Cutler Hammer	200	1MMx20RRL or RRLC	(where x=3-4)	1	Ov/Un	3-4	4/5	N	3,3a
Eaton-Cutler Hammer	200	1MP2204RRL or RRLC	1	Ov/Un	2-6	4	N	1,2	
Eaton-Cutler Hammer	200	1MPx206RRL or RRLC	(where x=3-6)	1	Ov/Un	2-6	4	N	1,2
Eaton-Cutler Hammer	200	3MMx20RRL or RRLC or R12RL	(where x=2-4)	1	Ov/Un	2-4	5	N	3,3a
Eaton-Cutler Hammer	200	CMB1212B200BTS FLCH	1	Ov/Un	1	4/5	N	1	
Eaton-Cutler Hammer	200	CMB1212L200BTS	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	200	CMB1212P200BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	200	CMB4242B200BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	200	CMB88B200BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	200	CMBB200BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	200	CMBP200BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	200	MB1212L200BTS	1	Ov/Un	1	4/5	N	1,2	
Eaton-Cutler Hammer	200	MB1212L200B TSA	1	Ov/Ln	1	4/5	N	1,2 AI	
Eaton-Cutler Hammer	200	MB2040B200BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	200	MB2040P200BTS FLCH	1	Ov/Un	1	4/5	N	1	
Eaton-Cutler Hammer	200	MB48B200BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	200	MB816B200BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	200	MB816P200BTS FLCH or BTSCU FLCH	1	Ov/Un	1	4/5	N	1	
Eaton-Cutler Hammer	200	MBB200BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	200	MBP200BTS FLCH	1	Ov/Un	1	4	N	1,2	
Eaton-Cutler Hammer	200	MBT48B200BTS	1	Ov/Un	1	4/5	N	1,2	

FPL - Florida Power Light PEF - Progress Energy-Florida TECO - Tampa Electric GULF - Gulf Power



Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number		Phase	Service	Pos	Term	Bypass	Config
Eaton-Cutler Hammer	200	MC1212L200BTSA		1	Ov/Un	1	4/5	N	1,2 AI
Eaton-Cutler Hammer	200	UAT-H4203x-FLCH	(where x=B or T)	1	Over	1	4	Y	1 AI
Eaton-Cutler Hammer	200	UAT-H5203x-FLCH	(where x=B or T)	1	Over	1	5	Y	3,3a AI
Eaton-Cutler Hammer	200	UAT-H7203x-FLCH	(where x=B or T)	3	Over	1	7	Y	4 AI
Eaton-Cutler Hammer	200	UAT-RS202B-FLCH		1	Over	1	4/5	N	1,2 AI
Eaton-Cutler Hammer	200	UAT-RS212C-FLCH		1	Ov/Un	1	4/5	N	1,2 AI
Eaton-Cutler Hammer	200	UAT-RS213A-FLCH		1	Under	1	4/5	N	1,2 AI
Eaton-Cutler Hammer	200	UAT-RS213C-FLCH		1	Ov/Un	1	4/5	N	1,2 AI
Eaton-Cutler Hammer	200	UAT-RS223A-FLCH		1	Under	1	4/5	N	1,2 AI
Eaton-Cutler Hammer	200	UAT-xR2332U-FLCH	(where x=2-3)	1	Ov/Un	2-3	4/5	N	1,2
Eaton-Cutler Hammer	200	UAT-y4213x-FLCH	(where y=E or H, where x=C or U)	1	Ov/Un	1	4	Y	1 AI
Eaton-Cutler Hammer	200	UAT-y5213x-FLCH	(where y=E or H, where x=C or U)	1	Ov/Un	1	5	Y	3,3a AI
Eaton-Cutler Hammer	200	UAT-y7213x-FLCH	(where y=E or H, where x=C or U)	3	Ov/Un	1	7	Y	4 AI
Eaton-Cutler Hammer	200	UT-4R2352U-FLCH		1	Ov/Un	4	4/5	N	1,2
Eaton-Cutler Hammer	200	UT-Hy203x-FLCH	(where y=E or H, where x=B or T)	3	Over	1	7	Y	4
Eaton-Cutler Hammer	200	UT-RS202B-FLCH		1	Over	1	4/5	N	1,2
Eaton-Cutler Hammer	200	UT-RS212C-FLCH		1	Ov/Un	1	4/5	N	1,2
Eaton-Cutler Hammer	200	UT-RS213A-FLCH		1	Under	1	4/5	N	1,2
Eaton-Cutler Hammer	200	UT-RS213C-FLCH		1	Ov/Un	1	4/5	N	1,2
Eaton-Cutler Hammer	200	UT-RS223A-FLCH		1	Under	1	4/5	N	1,2
Eaton-Cutler Hammer	200	UT-xR2332U-FLCH	(where x=2-3)	1	Ov/Un	2-3	4/5	N	1,2
Eaton-Cutler Hammer	200	UT-xR2392UU-FLCH	(where x=5-6)	1	Ov/Un	5-6	4/5	N	1,2
Eaton-Cutler Hammer	200	UT-y4203x-FLCH	(where y=E or H, where x=B or T)	1	Over	1	4	Y	1
Eaton-Cutler Hammer	200	UT-y4213x-FLCH	(where y=E or H, where x=C or U)	1	Ov/Un	1	4	Y	1
Eaton-Cutler Hammer	200	UT-y5203x-FLCH	(where y=E or H, where x=B or T)	1	Over	1	5	Y	3,3a
Eaton-Cutler Hammer	200	UT-y5213x-FLCH	(where y=E or H, where x=C or U)	1	Ov/Un	1	5	Y	3,3a
Eaton-Cutler Hammer	200	UT-y7213x-FLCH	(where y=E or H, where x=C or U)	3	Ov/Un	1	7	Y	4
Eaton-Cutler Hammer	225	35MMx20R12	(where x=1-4)	1	Ov/Un	1-4	5	Y	3,3a
Eaton-Cutler Hammer	225	37MMx20R12	(where x=1-4)	3	Ov/Un	1	7	Y	4
Eaton-Cutler Hammer	400	1008836x	(where x = CH or ECH)	1	Ov/Un	1	4	Y	1
Eaton-Cutler Hammer	400	1008837x	(where x = CH or ECH)	1	Ov/Un	1	4	Y	1 AI
Eaton-Cutler Hammer	400	35MM140R1240		1	Under	1	5	Y	3
Eaton-Cutler Hammer	400	35MM240R1240		1	Under	1	5	Y	3
Eaton-Cutler Hammer	400	37MM140R1240		3	Under	1	7	Y	4
Eaton-Cutler Hammer	400	37MM240R1240		3	Under	1	7	Y	4
Eaton-Cutler Hammer	400	CG1212P400BSL		1	Under	1	4	Y	1,2
Eaton-Cutler Hammer	400	CG404242SHL		1	Under	1	4	Y	1,2
Eaton-Cutler Hammer	400	CG40SHL		1	Under	1	4	Y	1,2
Eaton-Cutler Hammer	400	HP404040SHL		1	Under	1	4	Y	1,2

FPL - Florida Power Light PEF - Progress Energy-Florida TECO - Tampa Electric GULF - Gulf Power



Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Eaton-Cutler Hammer	400	HP40SHL	1	Under	1	4	Y	1,2
Eaton-Cutler Hammer	400	HP816Px00BSL (where x = 3 or 4)	1	Under	1	4	Y	1,2
Eaton-Cutler Hammer	400	UATH4330TFLCH	1	Ov/Un	1	4	Y	1 AI
Eaton-Cutler Hammer	400	UAT-y4300T-FLCH (where y=E or H)	1	Over	1	4	Y	1 AI
Eaton-Cutler Hammer	400	UAT-y5300T-FLCH (where y=E or H)	1	Over	1	5	Y	3,3a AI
Eaton-Cutler Hammer	400	UAT-y5330U-FLCH (where y=E or H)	1	Ov/Un	1	5	Y	3,3a AI
Eaton-Cutler Hammer	400	UAT-y7300T-FLCH (where y=E or H)	3	Over	1	7	Y	4 AI
Eaton-Cutler Hammer	400	UAT-y7330U-FLCH (where y=E or H)	3	Ov/Un	1	7	Y	4 AI
Eaton-Cutler Hammer	400	UTH4330TFLCH	1	Ov/Un	1	4	Y	1
Eaton-Cutler Hammer	400	UT-y4300T-FLCH (where y=E or H)	1	Over	1	4	Y	1
Eaton-Cutler Hammer	400	UT-y5300T-FLCH (where y=E or H)	1	Over	1	5	Y	3,3a
Eaton-Cutler Hammer	400	UT-y5330U-FLCH (where y=E or H)	1	Ov/Un	1	5	Y	3,3a
Eaton-Cutler Hammer	400	UT-y7300T-FLCH (where y=E or H)	3	Over	1	7	Y	4
Eaton-Cutler Hammer	400	UT-y7330U-FLCH (where y=E or H)	3	Ov/Un	1	7	Y	4
Eaton-Cutler Hammer	600	CH9526K7 (Requires Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5
Eaton-Cutler Hammer	600	CH9527K7 (Requires Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5 AI
Elec.Prod.	100	RVPD-xxxx-FPL	1	Under	2	4	N	1
Elec.Prod.	100	RVP-xxxx-FPL	1	Under	1	4	N	1
Elec.Prod.	200	MHPD-xxxx-FPL	1	Under	2	4	N	1
Elec.Prod.	200	MHP-xxxx-FPL	1	Under	1	4	N	1
Emerson	125	MESBGFXLW11FBZ1	1	Under	1	5	Y	3a
Emerson	125	MESBGFXLW11FBZ1P	1	Under	1	5	Y	3a
Emerson	125	MESBGFXLW11KBZ1	1	Under	1	5	Y	3a
Emerson	125	MESBGFXLW11KBZ1P	1	Under	1	5	Y	3a
Emerson	200	MESBAATLW11FBZ1	1	Under	1	5	Y	3a
Emerson	200	MESBAATLW11FBZ1P	1	Under	1	5	Y	3a
Emerson	200	MESBAATLW11KBZ1	1	Under	1	5	Y	3a
Emerson	200	MESBAATLW11KBZ1P	1	Under	1	5	Y	3a
General Electric	100	TM10RMCFMG	1	Ov/Un	1	4	N	1
General Electric	125	TM12RMCFMG	1	Ov/Un	1	4	N	1
General Electric	125	TMMR2212R	1	Under	2	4/5	N	1,2
General Electric	125	TMMR4x12R (where x=3-4)	1	Under	3-4	4/5	N	1,2
General Electric	125	TMMR6x12R (where x=5-6)	1	Under	5-6	4/5	N	1,2
General Electric	125	TMPR8x12R (where x=2-6)	1	Under	2-6	4/5	N	1,2
General Electric	150	TM15RMCFMG	1	Ov/Un	1	4	N	1
General Electric	150	TSMF415CSFL	1	Ov/Un	1	4/5	N	1,2
General Electric	150	TSMF815CSFL	1	Ov/Un	1	4/5	N	1,2
General Electric	150	TSMR415CSFLFMG	1	Ov/Un	1	4	N	1
General Electric	150	TSMR815CSFLFMG	1	Ov/Un	1	4	N	1

FPL - Florida Power Light PEF - Progress Energy-Florida TECO - Tampa Electric GULF - Gulf Power



Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number	Phase	Service	Pos	Term	Bypass	Config
General Electric	200	TM20RMCFMG	1	Ov/Un	1	4	N	1
General Electric	200	TMMR4x20R (where x=2-6)	1	Ov/Un	2-6	4	N	1,2
General Electric	200	TMMR6x20R (where x=3-6)	1	Under	3-6	4/5	N	1,2
General Electric	200	TMPR312x22R (where x=1-4)	3	Ov/Un	1-4	7	Y	4
General Electric	200	TMPR8x20R (where x=2-4)	1	Under	2-4	4/5	N	1,2
General Electric	200	TSLR1220FSAL	1	Ov/Un	1	4	N	1, AI
General Electric	200	TSMF420CSFL	1	Ov/Un	1	4/5	N	1,2
General Electric	200	TSMF820CSFL	1	Ov/Un	1	4/5	N	1,2
General Electric	200	TSMR2020CSCUFMG	1	Ov/Un	1	4	N	1
General Electric	200	TSMRx20CSFLFMG (where x = 4 or 8)	1	Ov/Un	1	4	N	1
General Electric	225	TMPR12x22R (where x=1-4)	1	Ov/Un	1-4	5	Y	3,3a
General Electric	400	TMPR1240RB	1	Ov/Un	1	5	Y	3,3a
General Electric	400	TMPR31240RB	3	Ov/Un	1	7	Y	4
General Electric	400	TSDR840USCU	1	Under	1	4/5	Y	1,2
Landis & Gyr/TALON	100	UAT111-XGF	1	Over	1	4/5	N	1
Landis & Gyr/TALON	100	UAT131-XGF	1	Over	1	4/5	N	1 AI
Landis & Gyr/TALON	125	UAT111-OGF	1	Over	1	4	N	1
Landis & Gyr/TALON	200	40005-01F	1	Over	1	5	Y	3,3a
Landis & Gyr/TALON	200	40007-01F	3	Over	1	7	Y	4
Landis & Gyr/TALON	200	40405-015F	1	Ov/Un	1	5	Y	3,3a
Landis & Gyr/TALON	200	40405-025F	1	Ov/Un	1	5	Y	3,3a
Landis & Gyr/TALON	200	40407-015F	3	Ov/Un	1	7	Y	4
Landis & Gyr/TALON	200	40407-025F	3	Ov/Un	1	7	Y	4
Landis & Gyr/TALON	200	41005-01F	1	Over	1	5	Y	3,3a
Landis & Gyr/TALON	200	41007-01F	3	Over	1	7	Y	4 AI
Landis & Gyr/TALON	200	41405-025F	1	Ov/Un	1	5	Y	3,3a AI
Landis & Gyr/TALON	200	41407-025F	3	Ov/Un	1	7	Y	4 AI
Landis & Gyr/TALON	200	LG0408B1200RT	1	Ov/Un	1	4	N	1
Landis & Gyr/TALON	200	LG0606L1200R or RA	1	Ov/Un	1	4/5	N	1, 1 AI
Landis & Gyr/TALON	200	UA27x6-ZGF (where x=1 or 3)	1	Ov/Un	2	1	N	1, 1 AI
Landis & Gyr/TALON	200	UA37x7-ZGF (where x=1 or 3)	1	Ov/Un	3	1	N	1, 1 AI
Landis & Gyr/TALON	200	UA47x9-ZGF (where x=1 or 3)	1	Ov/Un	4	1	N	1, 1 AI
Landis & Gyr/TALON	200	UA57x9-MGF (where x=1 or 3)	1	Ov/Un	5	1	N	1, 1 AI
Landis & Gyr/TALON	200	UA67x9-MGF (where x=1 or 3)	1	Ov/Un	6	1	N	1, 1 AI
Landis & Gyr/TALON	200	UAT317-OGF	1	Over	1	4/5	N	1
Landis & Gyr/TALON	200	UAT337-OGF	1	Over	1	4/5	N	1 AI
Landis & Gyr/TALON	200	UAT417-PGF	1	Under	1	4/5	N	1,2
Landis & Gyr/TALON	200	UAT417-XGF	1	Ov/Un	1	4/5	N	1,2
Landis & Gyr/TALON	200	UAT437-PGF	1	Under	1	4/5	N	1 AI



Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Landis & Gyr/TALON	200	UAT437-XGF	1	Ov/Un	1	4/5	N	1 AI
Landis & Gyr/TALON	400	41105-02FL	1	Ov/Un	1	5	Y	3,3a AI
Landis & Gyr/TALON	400	44707-02FL	3	Ov/Un	1	7	Y	4
Landis & Gyr/TALON	400	47705-02FL	1	Ov/Un	1	5	Y	3,3a
Landis & Gyr/TALON	400	49005-02FL	1	Ov/Un	1	5	Y	3,3a
Landis & Gyr/TALON	400	49007-02FL	3	Ov/Un	1	7	Y	4
Landis & Gyr/TALON	400	49105-02FL	1	Ov/Un	1	5	Y	3,3a AI
Landis & Gyr/TALON	400	49107-02FL	3	Ov/Un	1	7	Y	4 AI
Landis & Gyr/TALON	400	9817-8061 FPL Only	3	Under	3	7	N	4
Landis & Gyr/TALON	400	9817-8062 FPL Only	3	Under	3	7	N	4 AI
Landis & Gyr/TALON	600	9817-9526 (Requires Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5
Landis & Gyr/TALON	600	9817-9527 (Requires Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5 AI
Midwest	100	M0xxC010-FMG (where xx=32,36,38,41,51,55,76)	1	Over	1	4/5	N	1,2
Midwest	100	M0xxC010U-FMG (where xx=32,36,38,41,51,55,76)	1	Under	1	4/5	N	1,2
Midwest	100	M0xxC033-FMG (where xx=32,36,38,41,51,55,76)	1	Over	1	4/5	N	1,2
Midwest	100	M0xxC033U-FMG (where xx=32,36,38,41,51,55,76)	1	Under	1	4/5	N	1,2
Midwest	100	UTZ-6R1131C-FLMEP	1	Ov/Un	6	4/5	N	1,2
Midwest	100	UTZ-xR1121C-FLMEP (where x=2-5)	1	Ov/Un	2-5	4/5	N	1,2
Midwest	125	UATZ-RS101C-FLMEP	1	Ov/Un	1	4/5	N	1,2 AI
Midwest	125	UTZ-RS101C-FLMEP	1	Ov/Un	1	4/5	N	1,2
Midwest	150	R158CR2TLFMG	1	Ov/Un	1	4	N	1
Midwest	200	MPx00S0FMG (where x=1-4)	1	Under	1-4	4/5	N	1,2 AI
Midwest	200	MPx00S1FMG (where x=1-4)	1	Under	1-4	4/5	N	1,2 AI
Midwest	200	MPx20B0FMG (where x=1-4)	1	Under	1-4	4/5	N	1,2 AI
Midwest	200	MPx20B1FMG (where x=1-4)	1	Under	1-4	4/5	N	1,2 AI
Midwest	200	PM5x220B0FMG (where x=1-4)	1	Under	1-4	4/5	N	1,2 AI
Midwest	200	R208CR2TLFMG	1	Ov/Un	1	4	N	1
Midwest	200	R256EB118FMG	1	Ov/Un	1	4	N	1, AI
Midwest	200	R256EB1FMG	1	Ov/Un	1	4	N	1
Midwest	200	R256EB1NFMG	1	Ov/Un	1	4	N	1
Midwest	200	UAT-H4203x-FLMEP (where x=B or T)	1	Over	1	4	Y	1 AI
Midwest	200	UAT-H4213x-FLMEP (where x=C or U)	1	Ov/Un	1	4	Y	1 AI
Midwest	200	UAT-H5203x-FLMEP (where x=B or T)	1	Over	1	5	Y	3,3a AI
Midwest	200	UAT-H5213x-FLMEP (where x=C or U)	1	Ov/Un	1	5	Y	3,3a AI
Midwest	200	UAT-H7203x-FLMEP (where x=B or T)	3	Over	1	7	Y	4 AI
Midwest	200	UAT-H7213x-FLMEP (where x=C or U)	3	Ov/Un	1	7	Y	4 AI
Midwest	200	UAT-RS202B-FLMEP	1	Over	1	4/5	N	1,2 AI
Midwest	200	UAT-RS212C-FLMEP	1	Ov/Un	1	4/5	N	1,2 AI
Midwest	200	UAT-RS213A-FLMEP	1	Under	1	4/5	N	1,2 AI

FPL - Florida Power Light PEF - Progress Energy-Florida TECO - Tampa Electric GULF - Gulf Power



Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number		Phase	Service	Pos	Term	Bypass	Config
Midwest	200	UAT-RS213C-FLMEP		1	Ov/Un	1	4/5	N	1,2 AI
Midwest	200	UAT-RS223A-FLMEP		1	Under	1	4/5	N	1,2 AI
Midwest	200	UT-4R2352U-FLMEP		1	Ov/Un	4	4/5	N	1,2
Midwest	200	UT-H4203x-FLMEP	(where x=B or T)	1	Over	1	4	Y	1
Midwest	200	UT-H4213x-FLMEP	(where x=C or U)	1	Ov/Un	1	4	Y	1
Midwest	200	UT-H5203x-FLMEP	(where x=B or T)	1	Over	1	5	Y	3,3a
Midwest	200	UT-H5213x-FLMEP	(where x=C or U)	1	Ov/Un	1	5	Y	3,3a
Midwest	200	UT-H7203x-FLMEP	(where x=B or T)	3	Over	1	7	Y	4
Midwest	200	UT-H7213x-FLMEP	(where x=C or U)	3	Ov/Un	1	7	Y	4
Midwest	200	UT-RS202B-FLMEP		1	Over	1	4/5	N	1,2
Midwest	200	UT-RS212C-FLMEP		1	Ov/Un	1	4/5	N	1,2
Midwest	200	UT-RS213A-FLMEP		1	Under	1	4/5	N	1,2
Midwest	200	UT-RS213C-FLMEP		1	Ov/Un	1	4/5	N	1,2
Midwest	200	UT-RS223A-FLMEP		1	Under	1	4/5	N	1,2
Midwest	200	UT-xR2332U-FLMEP	(where x=2-3)	1	Ov/Un	2-3	4/5	N	1,2
Midwest	200	UT-xR2392UU-FLMEP	(where x=5-6)	1	Ov/Un	5-6	4/5	N	1,2
Midwest	400	1008836MEP		1	Ov/Un	1	4	Y	1
Midwest	400	1008837MEP		1	Ov/Un	1	4	Y	1 AI
Midwest	400	RS455***FMG		1	Under	1	4/5	Y	1,2
Midwest	400	UAT-H4300T-FLMEP		1	Over	1	4	Y	1 AI
Midwest	400	UAT-H5300T-FLMEP		1	Over	1	5	Y	3,3a AI
Midwest	400	UAT-H5330U-FLMEP		1	Ov/Un	1	5	Y	3,3a AI
Midwest	400	UAT-H7300T-FLMEP		3	Over	1	7	Y	4 AI
Midwest	400	UAT-H7330U-FLMEP		3	Ov/Un	1	7	Y	4 AI
Midwest	400	UT-H4300T-FLMEP		1	Over	1	4	Y	1
Midwest	400	UT-H5300T-FLMEP		1	Over	1	5	Y	3,3a
Midwest	400	UT-H5330U-FLMEP		1	Ov/Un	1	5	Y	3,3a
Midwest	400	UT-H7300T-FLMEP		3	Over	1	7	Y	4
Midwest	400	UT-H7330U-FLMEP		3	Ov/Un	1	7	Y	4
Milbank	100	U349y-XL-HSP	(where y=2-6)	1	Ov/Un	2-6	4/5	N	1,2
Milbank	100	U513y-O-100P-FMG	(where y=6-7)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	100	U513y-O-100S-FMG	(where y=6-7)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	100	UAP349y-XL-HSP	(where y=2-6)	1	Ov/Un	2-6	4/5	N	1,2 AI
Milbank	125	U285y-X-HSP	(where y=2-6)	1	Ov/Un	2-6	4/5	N	1,2
Milbank	125	U3505-XL-HSP		1	Ov/Un	1	5	Y	3,3a
Milbank	125	U3505-XL-TG-HSP		1	Ov/Un	1	5	Y	3,3a
Milbank	125	U3506-XL-TG-HSP		3	Ov/Un	1	7	Y	4
Milbank	125	U513y-O-125P-FMG	(where y=6-7)	1	Under	1-2	4/5	N	1,2
Milbank	125	U513y-O-125S-FMG	(where y=6-7)	1	Under	1-2	4/5	N	1,2

FPL - Florida Power Light PEF - Progress Energy-Florida TECO - Tampa Electric GULF - Gulf Power





Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Milbank	125	U8435-XL-TG-HSP	1	Over	1	4/5	N	1,2
Milbank	125	UAP3505-XL-TG-HSP	1	Ov/Un	1	5	Y	3,3a AI
Milbank	125	UAP3506-XL-TG-HSP	3	Ov/Un	1	7	Y	4 AI
Milbank	125	UAP8435-XL-TG-HSP	1	Ov/Un	1	4/5	N	1,2 AI
Milbank	150	U123y-X-HSP (where y=2-6)	1	Ov/Un	2-6	4/5	N	1,2
Milbank	150	U3312-XL-TG-HSP	1	Ov/Un	1	4/5	N	1,2
Milbank	150	U513y-O-150P-FMG (where y=6-7)	1	Under	1-2	4/5	N	1,2
Milbank	150	U513y-O-150S-FMG (where y=6-7)	1	Under	1-2	4/5	N	1,2
Milbank	150	UAP123y-X-HSP (where y=2-3)	1	Ov/Un	2-3	4/5	N	1,2 AI
Milbank	200	U125Y-X-HSP (where y=2-6)	1	Ov/Un	2-6	4/5	N	1,2
Milbank	200	U1980-O-HSP	1	Under	1	4/5	N	1,2
Milbank	200	U273y-XT-HSP (where y=2-6)	3	Ov/Un	2-6	7	Y	4
Milbank	200	U286y-X-HSP (where y=2-6)	1	Ov/Un	2-6	4/5	N	1,2
Milbank	200	U287y-XT-HSP (where y=2-6)	1	Ov/Un	2-6	5	Y	3,3a
Milbank	200	U3296-X-HSP	1	Ov/Un	1	5	Y	3,3a
Milbank	200	U3306-X-HSP	3	Ov/Un	1	7	Y	4
Milbank	200	U3850-XL-TG-HSP-PL	1	Ov/Un	1	4/5	N	1,2
Milbank	200	U5136-O-yyy-FMG (where yyy=41,55,75,332,552)	1	Un-Ped	1	4/5	N	1,2
Milbank	200	U5137-O-yyy-FMG (where yyy=41,55,75,332,552)	1	Un-Ped	2	4/5	N	1,2
Milbank	200	U513y-O-200P-FMG (where y=6-7)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	200	U513y-O-200S-FMG (where y=6-7)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	200	U513y-O-FMG (where y=6-7)	1	Un-Ped	1-2	4/5	N	1,2
Milbank	200	U7021-RL-TG-HSP	1	Over	1	4/5	N	1,2
Milbank	200	U7040-O-TG-HSP	1	Under	1	4	N	1,2
Milbank	200	U7040-XL-TG-HSP	1	Ov/Un	1	4/5	N	1,2
Milbank	200	U7043-XL-TG	1	Ov/Un	1	4/5	N	1,2
Milbank	200	U9550-RRL-QG-HSP	1	Over	1	5	Y	3,3a
Milbank	200	U9551-X-QG-HSP	1	Ov/Un	1	5	Y	3,3a
Milbank	200	U9700-RRL-QG-HSP	3	Over	1	7	Y	4
Milbank	200	U9701-X-QG-HSP	3	Ov/Un	1	7	Y	4
Milbank	200	U9801-X-QG -HSP	1	Ov/Un	1	4	Y	1,2
Milbank	200	UAP125y-X-HSP (where y=2-6)	1	Ov/Un	2-6	4/5	Y	1,2 AI
Milbank	200	UAP1980-O-HSP	1	Under	1	4/5	N	1,2 AI
Milbank	200	UAP3296-X-HSP	1	Ov/Un	1	5	Y	3,3a AI
Milbank	200	UAP3306-X-HSP	3	Ov/Un	1	7	Y	4 AI
Milbank	200	UAP5024-XL	1	Ov/Un	1	4	N	1
Milbank	200	UAP5024-XL-FMG	1	Ov/Un	1	4	N	1
Milbank	200	UAP7021-RL-TG-HSP	1	Over	1	4/5	N	1,2 AI
Milbank	200	UAP7040-O-TG-HSP	1	Under	1	4/5	N	1,2 AI



Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Milbank	200	UAP7040-XL-TG-HSP	1	Ov/Un	1	4/5	N	1,2 AI
Milbank	200	UAP9550-RRL-QG-HSP	1	Over	1	5	Y	3,3a AI
Milbank	200	UAP9551-X-QG-HSP	1	Ov/Un	1	5	Y	3,3a AI
Milbank	200	UAP9700-RRL-QG-HSP	3	Over	1	7	Y	4 AI
Milbank	200	UAP9701-X-QG-HSP	3	Ov/Un	1	7	Y	4 AI
Milbank	400	U2120-O-HSP	3	Ov/Un	1	7	Y	4
Milbank	400	U2120-X-HSP	3	Under	1	7	Y	4
Milbank	400	U2124-O-HSP	1	Under	1	4/5	Y	4
Milbank	400	U3313-X-HSP	1	Ov/Un	1	5	Y	3,3a
Milbank	400	U3566-X-HSP	3	Ov/Un	1	7	Y	4
Milbank	400	U3949-X-HSP	1	Over	1	5	Y	3,3a
Milbank	400	U5864-X-HSP	1	Ov/Un	1	5	Y	3, 3a
Milbank	400	U5864-X-HSP	1	Ov/Un	1	5	Y	3, 3a
Milbank	400	UAP2124-O-HSP	1	Under	1	4/5	Y	4 AI
Milbank	400	UAP3313-X-HSP	1	Ov/Un	1	5	Y	3,3a AI
Milbank	400	UAP3566-X-HSP	3	Ov/Un	1	7	Y	4 AI
Milbank	400	UAP3949-X-HSP	1	Over	1	5	Y	3,3a AI
Milbank	400	UAP5864-X-HSP	1	Ov/Un	1	5	Y	3, 3a AI
Milbank	600	U4667-X-8528 (Req. Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5
Milbank	600	U4667-XT-9526(Requires Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5
Milbank	600	UA4667-X-8529 (Req. Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5 AI
Milbank	600	UA4667-XT-9527(Requires Ridged Lugs) FPL ONLY	3	Ov/Un	1	7	Y	5 AI
Murray	100	RJ103AXF	1	Over	1	4	N	1
Murray	125	JA1224B1125	1	Ov/Un	1	4/5	N	1,2
Murray	150	JA0408B1150T or RT	1	Ov/Un	1	4	N	1
Murray	150	JA0816B1150CT or RCT	1	Ov/Un	1	4	N	1
Murray	150	JA0816B1150TH	1	Ov/Un	1	4/5	N	1,2
Murray	150	JA2040B1150	1	Ov/Un	1	4/5	N	1,2
Murray	150	JA2040B1150RC	1	Ov/Un	1	4	N	1
Murray	150	JA204LS	1	Ov/Un	1	4/5	N	1,2
Murray	150	JC0202B1150	1	Ov/Un	1	4/5	N	1,2
Murray	200	JA0408B1200T or RT	1	Ov/Un	1	4	N	1
Murray	200	JA0606L1200R or RA	1	Ov/Un	1	4/5	N	1, 1 AI
Murray	200	JA0816B1200CT or RCT	1	Ov/Un	1	4	N	1
Murray	200	JA0816B1200TH	1	Ov/Un	1	4/5	N	1,2
Murray	200	JA2040B1200	1	Ov/Un	1	4/5	N	1,2
Murray	200	JA2040B1200RC	1	Ov/Un	1	4	N	1
Murray	200	JA204TS	1	Ov/Un	1	4/5	N	1,2
Murray	200	JC0202B1200	1	Ov/Un	1	4/5	N	1,2

FPL - Florida Power Light PEF - Progress Energy-Florida TECO - Tampa Electric GULF - Gulf Power



Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Murray	200	RB103AR	1	Ov/Un	1	4/5	N	1,2
Murray	200	RH173CRF	1	Ov/Un	1	5	Y	3,3a
Murray	200	RH173GRF	3	Ov/Un	1	7	Y	4
Murray	200	RS103AVF	1	Under	1	4/5	N	1,2
Murray	200	RS103AXF	1	Over	1	4	N	1
Murray	400	JA0816B1350RLTM	1	Ov/Un	1	4/5	Y	1,2
Murray	400	JA0816B1400RLTM	1	Ov/Un	1	4/5	Y	1,2
Murray	400	JC0404L1400RLM	1	Ov/Un	1	4/5	Y	1,2
Murray	400	JC0408B1400RLTM	1	Ov/Un	1	4/5	Y	1,2
Siemens	100	WMLx3225RJ (where x=1-4)	3	Under	1-4	7	Y	4
Siemens	125	MC1224B1125	1	Ov/Un	1	4/5	N	1,2
Siemens	125	SPxx11RJ (where xx=22, 33, 44, 45, 46, 65, 66)	1	Ov/Un	2-6	4/5	N	1,2
Siemens	125	SUAT111-OGF	1	Over	1	4	N	1
Siemens	125	WMMx1125R (where x=2-6)	1	Under	2-6	4	N	1,2
Siemens	125	WMMx2125RJ (where x=2-6)	3	Under	2-6	5	N	2
Siemens	150	MC0408B1150T or RT	1	Ov/Un	1	4	N	1
Siemens	150	MC0408MB1150T	1	Ov/Un	1	4/5	N	1,2
Siemens	150	MC0816B1150CT or RCT	1	Ov/Un	1	4	N	1
Siemens	150	MC0816B1150TH	1	Ov/Un	1	4/5	N	1,2
Siemens	150	MC2040B1150	1	Ov/Un	1	4/5	N	1,2
Siemens	150	MC2040B1150RC	1	Ov/Un	1	4	N	1
Siemens	150	MM0202B1150	1	Ov/Un	1	4/5	N	1,2 St
Siemens	200	MC0408B1200T or RT	1	Ov/Un	1	4	N	1
Siemens	200	MC0408MB1200T	1	Ov/Un	1	4/5	N	1,2
Siemens	200	MC0606L1200R or RA	1	Ov/Un	1	4/5	N	1, 1 AI
Siemens	200	MC0816B1200CT or RCT	1	Ov/Un	1	4	N	1
Siemens	200	MC0816B1200TH	1	Ov/Un	1	4/5	N	1,2
Siemens	200	MC2040B1200	1	Ov/Un	1	4/5	N	1,2
Siemens	200	MC2040B1200RC	1	Ov/Un	1	4	N	1
Siemens	200	MM0202B1200	1	Ov/Un	1	4/5	N	1,2 St
Siemens	200	MM0406L1200H	1	Ov/Un	1	4/5	N	1,2
Siemens	200	S40405-015F	1	Ov/Un	1	5	Y	3,3a
Siemens	200	S40407-015F	3	Ov/Un	1	7	Y	4
Siemens	200	SPxx12RJ (where xx=42, 43, 44, 65, 66)	1	Ov/Un	2-6	4/5	N	1,2
Siemens	200	SUAT317-OGF	1	Over	1	4	N	1
Siemens	200	SUAT417-PGF	1	Under	1	4/5	N	1,2
Siemens	200	SUAT417-XGF	1	Ov/Un	1	4/5	N	1,2
Siemens	200	WMLx3200RJ (where x=1-4)	3	Under	1-4	7	Y	4
Siemens	200	WMMx1225R (where x=2-6)	1	Under	2-6	4	N	3



Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number	Phase	Service	Pos	Term	Bypass	Config
Siemens	200	WMMx2225RJ (where x=2-6)	3	Under	2-6	5	N	3a
Siemens	225	WML1x225RJ (where x=1-4)	1	Ov/Un	1-4	4	Y	3,3a
Siemens	225	WMLx1225RJ (where x=2-6)	1	Ov/Un	2-6	4	Y	3,3a
Siemens	225	WMLx2yz225RJ (where x=2 or 4) (yz=AB, BC or CA)	1	Ov/Un	2 or 4	5	Y	3, 3A
Siemens	400	MC0408B1400RLTM	1	Ov/Un	1	4/5	Y	1,2
Siemens	400	MC0816B1350RLTM	1	Ov/Un	1	4/5	Y	1,2
Siemens	400	MC0816B1400RLTM	1	Ov/Un	1	4/5	Y	1,2
Siemens	400	MM0404L1400RLM	1	Ov/Un	1	4/5	Y	1,2
Siemens	400	S9817-8061 FPL Only	3	Under	3	7	N	4
Siemens	400	S9817-8062 FPL Only	3	Under	3	7	N	4 Al
Siemens	400	WMKxy400z where (x=1 or 2)(y=1-3)(z=R or RJ) FPL Only	1	Under	1	4	Y	1
Siemens	400	WMLxy400RJ where (x=1 or 2) (y=1-3) FPL Only	1	Under	1	4	Y	1
Siemens	600	WMKxy600z where (x=1 or 2)(y=1-3)(z=R or RJ) FPL Only	1	Under	1	4	N	1
Square D	100	UTZ-6R1131C-FLSQD	1	Ov/Un	6	4/5	N	1,2
Square D	100	UTZ-xR1121C-FLSQD (where x=2-5)	1	Ov/Un	2-5	4/5	N	1,2
Square D	125	EZMR11y125 (where y=3-6)	1	Mtr Ctr	3-6	5	N	1,2
Square D	125	EZMR11y125CU (where y=3-6)	1	Mtr Ctr	3-6	5	N	1,2
Square D	125	EZMR11y125X (where y=3-6)	1	Mtr Ctr	3-6	5	N	1,2
Square D	125	EZMR31y125 (where y=3-5)	1	Mtr Ctr	3-5	5	N	1,2
Square D	125	EZMR31y125CU (where y=3-5)	1	Mtr Ctr	3-5	5	N	1,2
Square D	125	EZMR31y125X (where y=3-5)	1	Mtr Ctr	3	5	N	1,2
Square D	125	MPRyy125 (where yy=22,33,44,55,66)	1	Ov/Un	2-6	5	N	1,2
Square D	125	UATZ-RS101C-FLSQD	1	Ov/Un	1	4/5	N	1,2 Al
Square D	125	UTZ-RS101C-FLSQD	1	Ov/Un	1	4/5	N	1,2
Square D	150	QC816F150C	1	Ov/Un	1	4/5	N	1,2
Square D	150	RC816F150C	1	Ov/Un	1	4/5	N	1,2
Square D	200	EZML11y200 (where y=1-4)	1	Mtr Ctr	1-4	5	Y	1,2
Square D	200	EZML31y200 (where y=2-4)	1	Mtr Ctr	2-4	5	Y	3a
Square D	200	EZML33y200 (where y=1-4)	3	Mtr Ctr	1	7	Y	4
Square D	200	EZMR11y200 (where y=2-4)	1	Mtr Ctr	2-4	5	N	1,2
Square D	200	EZMR11y200CU (where y=2-4)	1	Mtr Ctr	2	5	N	1,2
Square D	200	EZMR11y200X (where y=2-4)	1	Mtr Ctr	2	5	N	1,2
Square D	200	MPLyy200 (where yy=32,43,64)	1	Ov/Un	2-4	5	Y	3
Square D	200	MPR4y200 (where y=2-3)	1	Ov/Un	2-3	5	N	1,2
Square D	200	MPR64200	1	Ov/Un	4	5	N	1,2
Square D	200	MPR8y200 (where y=5-6)	1	Ov/Un	5-6	5	N	1,2
Square D	200	QC12L200C	1	Ov/Un	1	4/5	N	1,2
Square D	200	QC2442M200C	1	Ov/Un	1	4/5	Y/N	1,2
Square D	200	QC816F200C	1	Ov/Un	1	4/5	N	1,2

FPL - Florida Power Light PEF - Progress Energy-Florida TECO - Tampa Electric GULF - Gulf Power



Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number		Phase	Service	Pos	Term	Bypass	Config
Square D	200	RC12L200C		1	Ov/Un	1	4/5	N	1,2
Square D	200	RC2040M200C		1	Ov/Un	1	4/5	N	1,2
Square D	200	RC816F200C		1	Ov/Un	1	4/5	N	1,2
Square D	200	UAT-H4203x-FLSQD	(where x=B or T)	1	Over	1	4	Y	1 AI
Square D	200	UAT-H4213x-FLSQD	(where x=C or U)	1	Ov/Un	1	4	Y	1 AI
Square D	200	UAT-H5203x-FLSQD	(where x=B or T)	1	Over	1	5	Y	3,3a AI
Square D	200	UAT-H5213x-FLSQD	(where x=C or U)	1	Ov/Un	1	5	Y	3,3a AI
Square D	200	UAT-H7203x-FLSQD	(where x=B or T)	3	Over	1	7	Y	4 AI
Square D	200	UAT-H7213x-FLSQD	(where x=C or U)	3	Ov/Un	1	7	Y	4 AI
Square D	200	UAT-RS202B-FLSQD		1	Over	1	4/5	N	1,2 AI
Square D	200	UAT-RS212C-FLSQD		1	Ov/Un	1	4/5	N	1,2 AI
Square D	200	UAT-RS213A-FLSQD		1	Under	1	4/5	N	1,2 AI
Square D	200	UAT-RS213C-FLSQD		1	Ov/Un	1	4/5	N	1,2 AI
Square D	200	UAT-RS223A-FLSQD		1	Under	1	4/5	N	1,2 AI
Square D	200	UT-4R2352U-FLSQD		1	Ov/Un	4	4/5	N	1,2
Square D	200	UT-H4203x-FLSQD	(where x=B or T)	1	Over	1	4	Y	1
Square D	200	UT-H4213x-FLSQD	(where x=C or U)	1	Ov/Un	1	4	Y	1
Square D	200	UT-H5203x-FLSQD	(where x=B or T)	1	Over	1	5	Y	3,3a
Square D	200	UT-H5213x-FLSQD	(where x=C or U)	1	Ov/Un	1	5	Y	3,3a
Square D	200	UT-H7203x-FLSQD	(where x=B or T)	3	Over	1	7	Y	4
Square D	200	UT-H7213x-FLSQD	(where x=C or U)	3	Ov/Un	1	7	Y	4
Square D	200	UT-RS202B-FLSQD		1	Over	1	4/5	N	1,2
Square D	200	UT-RS212C-FLSQD		1	Ov/Un	1	4/5	N	1,2
Square D	200	UT-RS213A-FLSQD		1	Under	1	4/5	N	1,2
Square D	200	UT-RS213C-FLSQD		1	Ov/Un	1	4/5	N	1,2
Square D	200	UT-RS223A-FLSQD		1	Under	1	4/5	N	1,2
Square D	200	UT-xR2332U-FLSQD	(where x=2-3)	1	Ov/Un	2-3	4/5	N	1,2
Square D	200	UT-xR2392UU-FLSQD	(where x=5-6)	1	Ov/Un	5-6	4/5	N	1,2
Square D	225	EZML11x225	(where x=1-4)	1	Mtr Ctr	1-4	5	Y	1,2
Square D	225	EZML31x225	(where x=2-4)	1	Mtr Ctr	2-4	5	Y	3a
Square D	225	EZML33x225	(where x=1-4)	3	Mtr Ctr	1	7	Y	4
Square D	225	EZMR11x200X	(where x=2-4)	1	Mtr Ctr	2	5	N	1,2
Square D	225	EZMR11x225	(where x=2-5)	1	Mtr Ctr	2-5	5	N	1,2
Square D	225	EZMR11x225CU	(where x=2-5)	1	Mtr Ctr	2-5	5	N	1,2
Square D	225	EZMR31x225	(where x=2-5)	1	Mtr Ctr	2-5	5	N	1,2
Square D	300	SU3040D300L	(with Red Dot retrofit label)	1	Under	1	4/5	Y	3
Square D	400	1008836SQD		1	Ov/Un	1	4	Y	1
Square D	400	1008837SQD		1	Ov/Un	1	4	Y	1 AI
Square D	400	CU12L400L	(with Red Dot retrofit label)	1	Under	1	4/5	Y	3



Participants: FPL, GULF, PEF, TECO

Approved Metering Equipment Enclosure List

Revised  
4/6/2012

Manufacturer	Amps	Catalog Number		Phase	Service	Pos	Term	Bypass	Config
Square D	400	EZML31y400	(where y=1-2)	1	Mtr Ctr	1-2	5	Y	3a
Square D	400	EZML33y400	(where y=1-2)	3	Mtr Ctr	1-2	7	Y	4
Square D	400	QU12L400xL	(where x = C or S)	1	Under	1	4/5	Y	3
Square D	400	QU816D400SL		1	Under	1	4/5	Y	3
Square D	400	SU3040D400L	(with Red Dot retrofit label)	1	Under	1	4/5	Y	3
Square D	400	UAT-H4300T-FLSQD		1	Over	1	4	Y	1 AI
Square D	400	UAT-H5300T-FLSQD		1	Over	1	5	Y	3,3a AI
Square D	400	UAT-H5330U-FLSQD		1	Ov/Un	1	5	Y	3,3a AI
Square D	400	UAT-H7300T-FLSQD		3	Over	1	7	Y	4 AI
Square D	400	UAT-H7330U-FLSQD		3	Ov/Un	1	7	Y	4 AI
Square D	400	UT-H4300T-FLSQD		1	Over	1	4	Y	1
Square D	400	UT-H5300T-FLSQD		1	Over	1	5	Y	3,3a
Square D	400	UT-H5330U-FLSQD		1	Ov/Un	1	5	Y	3,3a
Square D	400	UT-H7300T-FLSQD		3	Over	1	7	Y	4
Square D	400	UT-H7330U-FLSQD		3	Ov/Un	1	7	Y	4